


スイッチロック機能




U2 User manual

Danger and Warning

Please read the user manual before first use. DO NOT shine light directly into eyes. DO NOT cover the light head when the flashlight is on or place the light head on the ground. The heat dispersion of the light may cause damage to the flashlight itself or even result in burning other objects.

Inside the box



Optional Accessory



Specification


Table with 10 columns: FL1 STANDARD, Turbo, High, Medium, Low, ECO, Strobe, SOS. Rows include Output, Runtime, Beam Distance, LED, Reflector, Battery, Charging, Waterproof, Material, Dimension, Net Weight.

The above data has been measured in accordance with international flashlight testing standards ANSI/NEMA FL1 using 2*1NR 3.7V/3200mAh 18650 Lithium battery (total 6400mAh) under laboratory conditions.

Product Overview

The SPERAS U2 is a multifunctional flashlight that delivers a powerful 5000lm max output and reaches a 340m beam distance from its 3 Luminus SST40 LEDs and advanced driver. The rectangle shape provides a functional, modern and sturdy look and also enhances heat dissipation. USB-C 5V/3A ensures fast charging in under 2.25 hours for a full charge.

USB-C charging 5V/3A Side switch with power indicator




Operation Instructions

ON/OFF: Long press the side button to turn on the flashlight (enter the memory mode); long press the button again to turn off. Change modes: when the flashlight is ON, click the side button to change mode and circle (ECO-Low-Med-High-Turbo) with clicks. Strobes/SOS: at any state, double click to strobe, another double click will enter the SOS mode; click again will back the state before strobe.


Charging & Discharging

Charging: Open the USB rubber, insert the USB-C cable, connect your 5V/3A adapter then can charge the flashlight. When charging, the LED indicator shows red; when it's fully charged, shows green. When charging, press down the side switch to enter the ECO mode, press then release, turn OFF.




Discharging:

Insert the OTG connector to the USB-C port, connect the cable and then can discharge (max. 5V/3A) to phone or other electronics.



Press the latch and then remove the center part.

Install the center part with 3 pcs screws on the flashlight. Install the whole bike mount on the bike. Install the flashlight on the bike mount.




S1: ON/OFF/Momentary ON

In the OFF state, click the S1 button, the flashlight will turn on (enter the memory mode); click again, it will turn off.

S2/S3 Key The S2/S3 have the same function

When in the OFF state, press the any of S2 or S3 button, the flashlight will enter strobe mode, release will back OFF state.

In the ON state, click the any of S2 or S3 button, the flashlight will enter STROBE mode, release will back OFF state.



Power Indicator


Turn on the flashlight, the LED indication will automatically show as follows: 1. Red: charging 2. Green: is complete

How to use the wireless switch

Insert the acceptor to the USB-C port on the flashlight, and then click the acceptor to the USB-C port on the flashlight, and then the flashlight will turn on (enter the memory mode); click again, it will turn off.

B/C Key The B/C have the same function

When in the OFF state, press the any of B or C button, the flashlight will enter STROBE mode, release will back OFF state.



Power Indicator

Turn on the flashlight, the LED indication will automatically show as follows: 1. Red: charging 2. Green: is complete

Warranty

30 days free replacement: We will repair or replace a light within 30 days of purchase if it is afflicted with a manufacturing defect. If the problem calls for a replacement, we will replace the light with the same model as the one sent in. If the Series No. has been discontinued, customers will receive a product with similar or improved performance.


Beyond Warranty

Free warranty DOES NOT cover any damage or failure caused by: Normal wear up Damages caused by disassembling, modifying the flashlight

Shenzhen Speras Lighting Co., Ltd Add: 4F, Building G, Ganganren Innovation Park, Huaniang Road, Dalang Street, Longhua District, Shenzhen, China, China, 518109 Tel: +86-755-2107 2597 Email: info@speraslight.com Website: www.sperasflashlight.com



The SPERAS FLASHLIGHTS PERAS by a 5-year warranty. The SPERAS FLASHLIGHTS PERAS by a 5-year warranty. The SPERAS FLASHLIGHTS PERAS by a 5-year warranty.




U2 取扱説明書

安全上の注意

本製品は使用中に熱が発生し、本体及びヘッド部が高温になる場合がございます。使用上問題はありますが、ヘッド部にできるだけ接触しない様注意してください。

内容物の名称



別売アクセサリ




仕様

Table with 10 columns: ANSI標準, Turbo, High, Med, Low, Eco, Strobe, SOS. Rows include Output, Runtime, Beam Distance, LED, Reflector, Battery, Charging, Waterproof, Material, Dimension, Net Weight.

SPERAS 試験室でテストされたデータのデータは、SPERAS内蔵18650リチウムイオン充電電池×2個合計6400mAhを使用した場合のデータになります。

主な仕様と各部名称



ご利用方法


点灯-消灯 サイドスイッチを長押しするとON→OFF→ONと切り替わります。点灯時 サイドスイッチを押すとEco→Low→Med→High→Turboと切り替わります。指を離すと明るさモードが固定されます。

充電と給電について

充電方法 充電ポートカバーを開き、充電ポートにType-Cケーブルを挿入し、接続します。5V/3AのACアダプターで充電した場合約2.25時間でフル充電になります。

給電方法

OTG外部給電アダプタを接続した後、U2をモバイルバッテリーとして使用できます。



自転車ホルダの取付-取外し方法


①U2本体に④自転車ホルダ固定板を(幅の狭い方が照射側)3本のネジで取付けます。②自転車ホルダを⑥爪が照射側)U2本体の②自転車ホルダ固定板に固定します。



有線リモコンの使用法(別売品)

S1ボタン: 点灯/消灯/クイック点灯 消灯時、【S1】ボタンを押すとON→OFF→ONと切り替わります。点灯時、【A】ボタンを長押しして記憶した明るさモードで点灯→ボタンを離す→消灯

S2/S3ボタン: S2/S3ボタンは同じ機能を持っています。点灯時、【S2】 【S3】 ボタンのいずれかを押す。点灯時または消灯時、【S2】 【S3】 ボタンのいずれかを長押し→Strobeモードで点灯→ボタンを離す→元のモードで点灯または消灯。



無線リモコンの使用法(別売品)

Aボタン: 点灯/消灯/クイック点灯 消灯時、【A】ボタンを押すとON→OFF→ONと切り替わります。点灯時、【A】ボタンを長押しして記憶した明るさモードで点灯→ボタンを離す→消灯

B/Cボタン: B/Cボタンは同じ機能を持っています。点灯時、【B】 【C】 ボタンのいずれかを押す。点灯時または消灯時、【B】 【C】 ボタンのいずれかを長押し→Strobeモードで点灯→ボタンを離す→元のモードで点灯または消灯。



バッテリー残量の確認方法

電源を入れた後、サイドスイッチ/バッテリーインジケータが下記にて自動的に表示します。緑色点灯: 100% > C >= 70% (5秒間) オレンジ色点灯: 70% > C >= 50% (5秒間) 赤色点灯: 30% > C >= 5% (5秒間) 赤色点滅: 5% > C > 0% (消灯まで点滅)

メンテナンス


バッテリー残量不足の表示が出た場合、早急に充電してください。長期間使用しない場合は、本製品を換気の良い乾燥した場所にて保管してください。

日本国内保証規定

ご購入日から15日以内で、商品に不具合がある場合、お買い上げ店にて無料交換を申請することができます。ご購入日から1年以内に商品に不具合が発生した場合、無償修理、または同一品、同等品と無償交換いたします。

保証対象外について

※保証期間内でも次の場合は有償修理もしくは保証対象外となります。誤用・乱用及び取扱い不注意による故障。火災・地震・水害などの災害による故障。



商品型式: U2 シリアルNo. ご購入日: 販売店:

SPERASをお選びいただきありがとうございます。本製品は、購入日から1年間の保証が適用されます。販売店に購入日を記入してもらい、ご購入後に保証書に必要な事項を記載してください。

双面印刷 折后尺寸60x90mm